




BTA-70838S

Solar Adapter for SMP Battery

| F | ea | tu | re | s |
|---|----|----|----|----------|
| | | | - | <u> </u> |

- Solar adapter for charging one (1) or two (2) Soldier Modernization Program (SMP) batteries.
- This adapter when used in conjunction with the appropriate battery charger will charge one (1) or two (2) of the following batteries:
 - BT-70838, BT-70838xx in 5 hours or less
 - BT-70838-2/3xx in 4 hours or less





Related Products

BTC-70663 (Advanced Solar Charge Controller) BTC-70824-1 (Solar Charge Controller)

| Technical Specifications | | | |
|--------------------------|---------|---|--|
| National Stock Number | | 6150-01-609-0348 | |
| BT Part Number | | BTA-70838S | |
| Dimensions | Adapter | Length: 3.0 in (77 mm) Width: 0.9 in (23 mm) Height: 1.1 in (28 mm) | |
| | Cable | Length: 6.0 in (152 mm) | |
| Weight | | 0.6 lbs (0.27 kg) | |
| Storage Temperature | | -55°C to +71°C (-67°F to +145°F) | |
| Material/Color | | Modified ABS Plastic / Black | |
| Disposal | | Check local regulations (Contains 0% Mercury or Cadmium) | |

Bren-Tronics is an advanced designer and manufacturer of primary and rechargeable batteries, chargers and complete energy storage systems from watt hours to megawatt hours.

For a complete description of our products refer to Bren-Tronics website at: http://www.bren-tronics.com



HEADQUARTERS United States 10 Brayton Court, Commack, NY 11725

Phone: 1-631-499-5155 • Fax: 1-631-499-5504

Europe • 20 rue Henri Regnault 75014, Paris, France • Phone: +33(0)1-40-59-8051 • Fax: +33(0)1-45-41-5816 United Kingdom • 7 Airfield House, Kingston Business Park, Kingston Bagpuize, Oxon OX13 5FD • Phone: +44-1865-822322 • Fax: +44-1865-822301

Data presented in this document is subject to change without notice. This is for marketing and sales purposes only. This is not a controlled document. Please contact Bren-Tronics for latest specifications.