



## TECHNICAL DATASHEET

### BTA-70100-AC-x Series

### CABLE, ABC, AC POWER





BTA-70100-AC-1A shown on picture

#### Features

- The BTA-70100-AC-x Series of standard 120Vac & 220Vac cables used for powering the Advanced Battery Charger (ABC).

- Available AC power cable configurations include:  
BTA-70100-AC-1, 10FT, NEMA5-15P (US) TERMINAL  
BTA-70100-AC-1A, 6FT, NEMA5-15P (US) TERMINAL  
BTA-70100-AC-2, 6FT, CEE 7/7 (EU) TERMINAL  
BTA-70100-AC-3, 6FT, BS 1363 (UK) TERMINAL  
BTA-70100-AC-4, 6FT, AS/NZS 3112 (AU) TERMINAL

TERMINAL	ILLUSTRATIONS	
NEMA5-15P (US)		
CEE 7/7 (EU)		
BS 1363 (UK)		
AS/NZS 3112 (AU)		

#### Related Products

BTC-70100 (Advanced Battery Charger)



#### Technical Specifications

National Stock Number	Pending
BT Part Number	BTA-70100-AC-x Series
Dimensions	<b>Cable Length:</b> 72 in (1.8 m)
Weight	0.66 lbs (0.3 kg) for 6' Cable; 0.97 lbs (0.4 kg) for 10' Cable
Operating Temperature	-20°C to +50°C (-4°F to +122°F)
Storage Temperature	-40°C to +70°C (-40°F to +158°F)
Material/Color	Rubber with Metal Connector/Black
Disposal	Check local regulations (Contains 0% Mercury or Cadmium)

Bren-Tronics is an advanced designer and manufacturer of primary and rechargeable batteries, chargers and complete energy storage systems from watt hours to megawatt hours.

For a complete description of our products refer to Bren-Tronics website at: <http://www.bren-tronics.com>



#### HEADQUARTERS

##### United States

10 Brayton Court, Commack, NY 11725  
Phone: 1-631-499-5155 • Fax: 1-631-499-5504

Europe • 20 rue Henri Regnault 75014, Paris, France • Phone: +33(0)1-40-59-8051 • Fax: +33(0)1-45-41-5816

United Kingdom • 7 Airfield House, Kingston Business Park, Kingston Bagpuize, Oxon OX13 5FD • Phone: +44-1865-822322 • Fax: +44-1865-822301

Data presented in this document is subject to change without notice. This is for marketing and sales purposes only. This is not a controlled document. Please contact Bren-Tronics for latest specifications.