

TECHNICAL DATASHEET

BTA-70100-DCB

Bren-Tronics ABC Charges





ADAPTER, ABC, DUAL DEWALT®* DCB

Features

- The BTA-70100-DCB adapter when used in conjunction with BTC-70100, Advanced Battery Charger (ABC), will simultaniously charge one or two of the following DEWALT® * power tool batteries:
 - DCB201 20V, 1.5Ah
 - DCB203 20V, 2Ah
 - DCB205 20V. 5Ah
 - DCB606 20/60V, 6Ah
 - DCB609 20/60V, 9Ah
 - * DeWalt, the lined DeWalt design, and the yellow and black motif are Registered (R) Trademarks of Black & Decker Corporation. Use of these marks does not imply any affiliation with or endorsement by them.

Related Products

BTC-70100, Advanced Battery Charger (ABC)



Technical Specifications	
National Stock Number	6130-01-706-9395
BT Part Number	BTA-70100-DCB
Dimensions	Length: 8.0 in (203 mm) Width: 3.5in (89 mm) Height: 2.3 in (58 mm)
Weight	0.76 lbs (0.34 kg)
Operating Temperature	-20°C to +55°C (-4°F to +131°F)
Storage Temperature	-40°C to +70°C (-40°F to +158°F)
Material/Color	Modified ABS Plastic/Tan/Black
Disposal	Check local regulations (Contains 0% Mercury or Cadmium)

Bren-Tronics is an advanced designer and manufacturer of primary and rechargeable batteries, chargers and complete energy storage systems from watt hours to megawatt hours.

For a complete description of our products refer to Bren-Tronics website at: http://www.bren-tronics.com



HEADQUARTERS United States

10 Brayton Court, Commack, NY 11725 Phone: 1-631-499-5155 • Fax: 1-631-499-5504

Europe • 20 rue Henri Regnault 75014, Paris, France • Phone: +33(0)1-40-59-8051 • Fax: +33(0)1-45-41-5816 United Kingdom • 7 Airfield House, Kingston Business Park, Kingston Bagpuize, Oxon OX13 5FD • Phone: +44-1865-822322 • Fax: +44-1865-822301

Data presented in this document is subject to change without notice. This is for marketing and sales purposes only. This is not a controlled document. Please contact Bren-Tronics for latest specifications.