

BTA-70100-5

ADAPTER, ABC, BB-2600/2800/326



Features

- The BTA-70100-5 adapter when used in conjunction with BTC-70100 (Advanced Battery Charger) will charge any combination of one (1) to four (4) of the following batteries:
 - (2) BB-2600A/U
 - (2) BB-2800/U
 - (2) BB-326/U

Related Products

BTC-70100 (Advanced Battery Charger)



Technical Specifications

National Stock Number	6130-01-667-1598
BT Part Number	BTA-70100-5
Dimensions	Length: 8.0 in (203 mm) Width: 3.5 in (89 mm) Height: 2.3 in (58 mm)
Weight	0.9 lbs (0.41 kg)
Operating Temperature	-20°C to +55°C (-4°F to +131°F)
Storage Temperature	-40°C to +70°C (-40°F to +158°F)
Material/Color	Modified ABS Plastic/Tan/Black
Disposal	Check local regulations (Contains 0% Mercury or Cadmium)

Bren-Tronics is an advanced designer and manufacturer of primary and rechargeable batteries, chargers and complete energy storage systems from watt hours to megawatt hours.

For a complete description of our products refer to Bren-Tronics website at: <http://www.bren-tronics.com>



HEADQUARTERS

United States

10 Brayton Court, Commack, NY 11725
Phone: 1-631-499-5155 • Fax: 1-631-499-5504

Europe • 20 rue Henri Regnault 75014, Paris, France • Phone: +33(0)1-40-59-8051 • Fax: +33(0)1-45-41-5816

United Kingdom • 7 Airfield House, Kingston Business Park, Kingston Bagpuize, Oxon OX13 5FD • Phone: +44-1865-822322 • Fax: +44-1865-822301

Data presented in this document is subject to change without notice. This is for marketing and sales purposes only. This is not a controlled document. Please contact Bren-Tronics for latest specifications.