


TECHNICAL DATASHEET

BTK-350765-R2

6-PACK REVERSE BULKHEAD CONNECTOR, KIT, RoHS V2

Features

- The BTK-350765-R2 is a 6-PACK Booster/Inverter output connector.
- This size 24 bayonet connector utilizes male pin contacts for all power, control, and montitoring connections.
- Supports both series and parallel configurations of the 6-PACK, up to full-rated power.



Related Products

The BTK-350765-R2 mates the following 6-PACK accessories:
 BTA-70772-1(R2) - CABLE, BOOSTER, 6-PACK, (RoHS V2)
 BTA-70772-2(R2) - CABLE, DC INPUT, 6-PACK BOOSTER, (RoHS V2)
 BTA-70772-3(R2) - CABLE, BOOSTER, 6-PACK, 5M, (RoHS V2)
 BTA-70772-4R2 - CABLE, BOOSTER w/COMM, 12 FT, RoHS V2



N/A
BTK-350765-R2
Length: 1.7 in (43 mm) Width: 1.7 in (43 mm) Height: 1.4 in (35 mm)
0.20 lbs (0.09 kg)
-20°C to +50°C (-4°F to +122°F)
-40°C to +70°C (-40°F to +158°F)
Plastic/Metal Connector/Black
Check local regulations (Contains 0% Mercury)

Bren-Tronics is an advanced designer and manufacturer of primary and rechargeable batteries, chargers and complete energy storage systems from watt hours to megawatt hours.

For a complete description of our products refer to Bren-Tronics website at: http://www.bren-tronics.com



HEADQUARTERS

United States

10 Brayton Court, Commack, NY 11725 Phone: 1-631-499-5155 • Fax: 1-631-499-5504

Europe • 20 rue Henri Regnault 75014, Paris, France • Phone: +33(0)1-40-59-8051 • Fax: +33(0)1-45-41-5816

United Kingdom • 7 Airfield House, Kingston Business Park, Kingston Bagpuize, Oxon OX13 5FD • Phone: +44-1865-822322 • Fax: +44-1865-822301

Data presented in this document is subject to change without notice. This is for marketing and sales purposes only. This is not a controlled document. Please contact Bren-Tronics for latest specifications.