



BTC-70777

Combo Charger



Features

- The BTC-70777 is a state of the art combo battery charger designed for military vehicles.
- Specifically designed to withstand the rigors associated with operating in a moving vehicle.
- The charger is capable of charging up to 16 batteries in multiple combinations with easy to follow LED lighting sequences.
- The combo charger can charge a full complement of any combination of the following batteries in less than 7 hours:
 - Rifleman Radio Battery up to 16
 - MBITR (AN/PRC-148) up to 8
 - ALI-130 (BT-70716) up to 8
 - Harris Flacon (AN/PRC-152) up to 8
 - LI-80 Land Warrior (BT-70867BE or BT-70867BG) up to 4
 - LI-145 Land Warrior (BT-70868BK or BT-70868BE) up to 4
- Powered from 22V-34V DC, 240W max, 80V-270V AC, 47/65 Hz, 285 VA*

Related Products

- BTA-70864-2 (AC Input Cable, US, 12 ft) included
- BTA-70864-3 (AC Input Cable, US, 6 ft)
- BTA-70864-5 (AC Input Cable, Euro)
- BTA-70864-6 (AC Input Cable, UK)
- BTA-70777-4 (DC Input Cable)

*DC cables are not included

Technical Specifications

National Stock Number	6130-01-605-5858
BT Part Number	BTC-70777
Dimensions	Length: 15.8 in (400 mm) Width: 9.9 in (250 mm) Height: 10.0 in (254 mm)
Weight	20.0 Lbs (9.10 Kg)
Operating Temperature	-20°C to +50°C (-4°F to +122°F)
Storage Temperature	-40°C to +70°C (-40°F to +158°F)
Material/Color	Aluminum / Desert Tan
Disposal	Environmentally Safe – Contains Zero (0)% Mercury or Cadmium

For a complete description of our products refer to Bren-Tronics website at:
<http://www.bren-tronics.com>



United States

10 Brayton Court
Commack, NY 11725-3197
Phone: 1-631-499-5155
Fax: 1-631-499-5504

Europe

20 rue Henri Regnault 75014,
Paris, France
Phone: +33(0)1-40-59-8051
Fax: +33(0)1-45-41-5816

United Kingdom

Brunel House, Volunteer Way
Faringdon, Oxfordshire SN7 7YR
United Kingdom
Phone: +44-1367-246027
Fax: +44-1367-246041